


RS-232 To TTL Converter (MAX3232IDR)



Most of the MCUs use TTL levels, and the computer serial port generally uses 232 levels. If we want the computer to communicate with the MCU, we need this **RS-232 To TTL Converter (MAX3232IDR)**.

This module is based on Max3232, it supports multiple baud rate communication and theoretically supports communication up to 230400bps baud.

Version

Product Version	Changes	Released Date
RS-232 To TTL Conveter (MAX3232IDR)	Initial	Sep 2018

Feature

- Easy to use
- Stable, high speed
- High cost performance
- ± 15 -kV ESD Protection
- Low power consumption
- Two Drivers and Two Receivers

Specification

Item	Value
Supply Voltage	3.3V / 5V
Driver input voltage	0V ~ 5.5V
Receiver input voltage	-25V ~ +25V
Supply current(No load)	0.3mA
Operating free-air temperature	-40°C ~ 85°C
Storage temperature range	-65°C ~ 150°C
Maximum data rate	250 Kbit/s
Support baud rate	300bps ~ 230400bps
Size	L: 35mm W: 30mm H: 15mm
Weight	10.9g
Package size	L: 150mm W: 100mm H: 15mm
Gross Weight	14g



Attention


When using a higher baud rate, you need to pay attention to whether the connected MCU supports it.

Typical Applications

- Hand-Held Equipment
- Palmtop PCs


Hardware Overview

Pin Out



Getting Started

This is a simple module that only needs to connect the corresponding interface to the corresponding device to transfer data using the serial port tool. You should note that when connecting a TTL device, the RX pin of the module needs to be connected to the TX pin of the device, and vice versa, the TX pin of the module needs to be connected to the RX pin of the device.



Schematic Online Viewer